



Quick Start Up Guide

Initial Set Up:
Power Up The Remote Controller
Select System ID
Select Number of Columns
Position Columns
Power Up Each Column
System will Auto lock and run as a group

1) **Emergency Stop Button**
 Will Disable Remote Control Communications
 And Shut The Entire System Down
 Rotate Button To Restart The System Again

2) **Remote Control Power Button**

3) **Optional Accessory Column Lights On/Off**

4) **Digital Display:**
 System ID: All Columns Must Be On The
 Same System ID As The Remote
 Controller

5 3 System ID Example

Column Count: Lets You Set Up
 Number Of Columns

0 4 Column Count Example
 8 Column Max

P "P" Press Protect™ Prevents Accidental
 Activation Of The Remote Controller
 Press & Release Any Button To Re-Wake System

See Operation Instructions Decal For List Of
 Error Codes

5) **Selection And Enter Buttons**
 Used During Setup

6) **Joystick:**
 Up - Raise
 Partial Down - Slow Lower
 Full Down - Normal Lower

7) **Lower To Lock:**
 Lowers Columns Onto The Locks
 Green Light On Top Of Columns
 Will Illuminate When Engaged

8) **Remote Controller Power Indicator**

9) **Column Indicator Light:**
 **Yellow Flashing - Next Column
 Position To Add To System**

 **Yellow - Not Active Column**

 **Green - Active Column**

 **Red - Column with Error or
 Height Limit Reached**

10) **Column Buttons - Activate/Deactivate
 Pair of Columns**

11) **Lock/Unlock The Group Or
 Refresh/Wake Up The Group**

For Setup Video And Other Information:
<http://www.rotarylif.com/machflex/>

